



PV Array Breakers

System Components and Accessories



Features:

- DIN rail mount with set-screw compression terminals
- #14 to 2 AWG (1.62 to 6.54 mm diameter) clamp terminals
- DIN Rail End Clamp FW-EC-DIN accessory available

PV Array Breakers Specifications

02/2019

Model	Current Rating	Voltage Rating*	Terminals	Width (in/mm)
DIN-1-DC	1A	125VDC	Single pole	0.5 / 13
DIN-2-DC	2A	150VDC	Single pole	0.5 / 13
DIN-3-DC	3A	150VDC	Single pole	0.5 / 13
DIN-4-DC	4A	150VDC	Single pole	0.5 / 13
DIN-5-DC	5A	150VDC	Single pole	0.5 / 13
DIN-6-DC	6A	150VDC	Single pole	0.5 / 13
DIN-8-DC	8A	150VDC	Single pole	0.5 / 13
DIN9-DC	9A	150VDC	Single pole	0.5 / 13
DIN-10-DC	10A	150VDC	Single pole	0.5 / 13
DIN-15-DC	15A	150VDC	Single pole	0.5 / 13
DIN-20-DC	20A	125VDC	Single pole	0.5 / 13
DIN-30-DC	30A	125VDC	Single pole	0.5 / 13
DIN-50-DC	50A	125VDC	Single pole	0.5 / 13
DIN-60-DC	60A	125VDC	Single pole	0.5 / 13

*Approved for maximum VOC of 150VDC for PV array applications only

980-0054-01-00 REV A

www.outbackpower.com

OutBack reserves the right to make changes to the products and information contained in this document without notice. Copyright © 2019 OutBack Power. All Rights Reserved. OutBack is a registered trademark of Alpha Technologies Services, Inc.